

90+ LIGHTING



| | |
|-------|-------------------------------|
| MODEL | MR16 7W 480LM 3000K GU5.3 24D |
| SKU | SE-350.074 |

| DIMMER COMPATIBILITY LIST | | | | | | | | |
|---------------------------|----------------|---------------|-------------|-----------------|----------------|--------------------|--------------------|--------------------------------|
| MANUFACTURER | BRAND | DIMMER MODEL | TRANSFORMER | COMPATIBILITY | | | | |
| | | | | LIGHTECH LET-60 | HATCH RS12-60M | HATCH RS12-60M-LED | LIGHTECHINC LET 75 | Trancil - THLED 50W (MAGNETIC) |
| LUTRON | VIVE | MRF2S-6CL-WH | | - | NC | NC | - | - |
| | CASETA | PD-6WCL-WH | | - | NC | NC | - | - |
| | DIVA | DVELV-300P-WH | | OK | OK | OK | OK | OK |
| | | DVSCCL-153P | | OK | OK | NC | - | OK |
| | MAESTRO | MACL-153M-WH | | OK | OK | NC | - | NC |
| | | SCL-153P-WH | | OK | OK | NC | OK | OK |
| | SKYLARK | CTCL-153P | | OK | OK | NC | - | OK |
| | | SLV-600P | | - | OK | NC | - | - |
| | | RRD-6CL-WH | | OK | NC | NC | - | OK |
| | RADIO RA2 | RD-RD | | - | NC | NC | - | - |
| | | RRD-H6BRL | | - | NC | NC | - | - |
| | - | MRF2-3LD | | OK | NC | NC | OK | OK |
| | TOGGLER | TG-600PR | | OK | OK | NC | - | NC |
| | GRAPHIK EYE OS | QSGRJ-6P | | OK | OK | OK | - | OK |
| | GRAKIF EYE | - | | - | OK | OK | - | - |
| INOVAT | NTELV-300 | | - | OK | OK | - | - | |
| LEVITON | - | 6602-1W | | OK | OK | NC | - | NC |
| - | - | L20-6602 | | - | NC | NC | - | - |
| LEGRAND | PASS & SEYMOUR | DDH16PWV | | NC | NC | NC | - | NC |
| COOPER | COOPER | ASPIRE | | NC | NC | NC | - | NC |
| LUTRON | CREDENZA | TTCL-100 | | NC | NC | NC | - | NC |

DIMMER COMPATIBILITY

| | |
|----|------------------|
| OK | Dims to < 15% |
| OK | Dims to 15 - 30% |
| NC | Not Compatible |

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.