

90+ LIGHTING



MODEL	B11 3.3W 300LM 2200K E12
SKU	SE-350.118

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	VIVE	MRF2S-6CL-WH	OK	
	CASETA	PD-6WCL-WH	OK	
	DIVA	DV-600P-WH	OK	
	DIVA	DVELV-300P-WH	OK	
	DIVA C*L	DVWCL-153PH-WH	OK	
	MAESTRO	MAELV-600-WH	MAELV-600-WH	OK
		S-603P-WH	S-603P-WH	OK
	SKYLARK	SCL-153P-WH	SCL-153P-WH	OK
		SELV-300P-WH	SELV-300P-WH	OK
		SLV-600-WH	SLV-600-WH	OK
	SPACER	SPSELV-600M	SPSELV-600M	OK
	NOVA T	NTELV-300-WH	NTELV-300-WH	OK
		NTLV-600-277-WH	NTLV-600-277-WH	OK
	RADIO RA2	RRD-6CL-WH	RRD-6CL-WH	OK
-	CT-600PR-WH	CT-600PR-WH	OK	
ARIADNI	AYCL-153P-WH	AYCL-153P-WH	NC	
LEVITON	DECORA	R62-6674-P0W	OK	
	-	R70-6631-1LW	OK	
	-	C22-6672-1LW	OK	

DIMMER COMPATIBILITY	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 - 2) The results may be different for each application depending on the installation conditions.
 - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
 - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.