

90+ LIGHTING



| | |
|-------|-------------------------|
| MODEL | ST19 7W 800LM 2700K E26 |
| SKU | SE-RCL06.1107-A |

| DIMMER COMPATIBILITY LIST | | | |
|---------------------------|-------------------|-----------------|---------------|
| MANUFACTURER | BRAND | DIMMER MODEL | COMPATIBILITY |
| LUTRON | DIVA | DV-603P | OK |
| | | DVW-600PH-WH | NC |
| | | DV-603PH-WH | OK |
| | | DV-600PH-WH | OK |
| | | DVCL-153PH | NC |
| | | DVWCL-153PH-WHC | OK |
| | | DV-600P-WH | NC |
| | | DVCL-253PH | NC |
| | | DVCL-153P-WH | OK |
| | | DVELV-300P-WH | OK |
| | DIVA C+L | DVWCL-153PH-WH | OK |
| | | S-600 | NC |
| | SKYLARK | CTCL-153P-WH | OK |
| | | S-600PR-WH | OK |
| | | S-603PGH-WH | NC |
| | | S-600H-WH | NC |
| | | S-10PH | NC |
| | | SCL-153P-WH | NC |
| | | S-600-IV | OK |
| | | S-600-AL | OK |
| | | S-603PH-WH | OK |
| | | SCL-153PH-WH | OK |
| | | S-603P-WH | OK |
| | | SELV-300P-WH | OK |
| | | SLV-600-WH | OK |
| | | SPSELV-600M | OK |
| | MAESTRO | D-600PH-DK | NC |
| | | MAW-600 | NC |
| | | MAW-600H-AL | NC |
| | | MACL-153M-WH | NC |
| | | MACL-153MR-WH | NC |
| | | MACL-153MH-WH | NC |
| | | MSCL-OP153MH-WH | NC |
| | | TG-603PGH-WH | NC |
| | | MAELV-600-WH | OK |
| | | DV-603PR | OK |
| | TOGLER | D-600RH-DK | NC |
| | | TG-600PH-IV | NC |
| | | TGCL-153PH-WH | OK |
| | | D-600R-WH | OK |
| | ARIADNI | D-600R-IV | NC |
| | | DVCL-153P-WH-3 | OK |
| | | AYCL-153P-WH | OK |
| | | AY-600PH-WH | NC |
| | | AYCL-153PH | OK |
| | | CT-103P-WH | OK |
| | | S-600P-WH | OK |
| | | TG-600PNLH-WH | OK |
| | | LECL-153PH-WH | OK |
| | | MACL-153MLRH-WH | OK |
| VIVE | MRF2S-6CL-WH | OK | |
| | PD-6WCL-WH | OK | |
| NOVA T | NTELV-300-WH | OK | |
| | NTLV-600-277-WH | OK | |
| LEVITON | RADIO RA2 | RRD-6CL-WH | OK |
| | 6684 | | NC |
| | NO.6683 | | NC |
| | 6631-LA | | OK |
| | IPI06 | | NC |
| | S-600P-WH | | OK |
| | NO.6672 | | OK |
| | 603-6631-A | | OK |
| | 6631-A | | OK |
| | NO.IPL06 | | NC |
| | IPI10-1LZ | | NC |
| | 6683-10Z | | NC |
| | IPI06-1LZ | | OK |
| | NO.6631 | | OK |
| | 6681 | | NC |
| | DECORA | R62-6674-P0W | OK |
| GE | 18024 | OK | |
| ALMOND | LUXDM600-12 | OK | |
| AH | SDM3/1000 | OK | |
| | SDM/600 | NC | |
| LEGRAND | HCL453PTC | NC | |
| | DAL06P-C2-K | NC | |
| COOPER | TAL06P-C2-K | NC | |
| | SAL06P-W-K | NC | |
| | AAL06-C1 | NC | |
| MAXXIMA | MEW-DM600 | OK | |
| | DM600-12-3/LED/WH | OK | |
| CTL | DM600-12-3 | OK | |
| | ADPD453LW2 | OK | |
| ADORNE | ADWR703HW4 | OK | |
| | TAL06P1-C5 | OK | |
| EATON | | | OK |

| DIMMER COMPATIBILITY | |
|----------------------|------------------|
| OK | Dims to < 15% |
| OK | Dims to 15 - 30% |
| NC | Not Compatible |

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.