

90+ LIGHTING



MODEL	BR20 7W 525LM 2700K E26
SKU	SE-RCU01.1107-B

DIMMER COMPATIBILITY LIST					
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY		
LUTRON	DIVA	DV-603P	OK		
		DVW-600PH-WH	OK		
		DV-600PH-WH	OK		
		DVCL-153PH	NC		
		DV-603PH-WH	NC		
		DVCL-153P-WH	OK		
		DVWCL-153PH-WHC	OK		
		DV-600P-WH	NC		
		DVCL-253PH	NC		
		DVCL-153P-WH	OK		
	DVELV-300P-WH	OK			
	DVWCL-153PH-WH	OK			
	DIVA C+L	-	S-600	NC	
	SKYLARK	-	CTCL-153P-WH	OK	
			S-600PR-WH	OK	
			S-603PGH-WH	NC	
			S-600H-WH	NC	
			S-10PH	NC	
			SCL-153P-WH	NC	
			S-600-IV	OK	
			S-600-AL	NC	
			S-603PH-WH	OK	
			S-600P-WH	NC	
			SCL-153PH-WH	OK	
			SELV-300P-WH	OK	
			SLV-600-WH	OK	
			S-603P-WH	OK	
			D-600PH-DK	NC	
	MAESTRO	-	MAW-600	NC	
			MAW-600H-AL	NC	
			MACL-153M-WH	NC	
			MACL-153MR-WH	NC	
			MACL-153MH-WH	NC	
			MSCL-OP153MH-WH	NC	
			MACL-153MLH-WH	NC	
			TG-603PGH-WH	NC	
			MAELV-600-WH	OK	
			DV-603PR	OK	
	TOGLER	-	D-600RH-DK	NC	
			TG-600PH-WH	OK	
			TG-600PH-IV	NC	
			TGCL-153PH-WH	OK	
			D-600R-WH	NC	
	ARIADNI	-	D-600R-IV	NC	
			AYCL-153P-WH	OK	
			AY-600PH-WH	NC	
			AYCL-153PH	OK	
			MRF2S-6CL-WH	OK	
	VIVE	-	PD-6WCL-WH	OK	
			SPSELV-600M	OK	
SPACER	-	NTELV-300-WH	OK		
		NTLV-600-277-WH	OK		
NOVA T	-	RRD-6CL-WH	OK		
		RADIO RA2	OK		
LEVITON	-	DECORA	R62-6674-P0W	NC	
		6684	NC		
		NO.6683	NC		
		6631-LA	OK		
		IPI06	NC		
		S-600P-WH	OK		
		NO.6672	OK		
		603-6631-A	NC		
		6631-A	OK		
		NO.IPL06	OK		
		IPI10-1LZ	NC		
		6683-10Z	OK		
		IPI06-1LZ	OK		
		NO.6631	OK		
		6681	NC		
		18024	OK		
		GE	-	LUXDM600-12	OK
		ALMOND	-	DM600-12-3	OK
		CTL	-	SDM3/1000	NC
		AH	-	SDM/600	OK
LEGRAND	-	HCL453PTC	NC		
COOPER	-	DAL06P-C2-K	NC		
		TAL06P-C2-K	NC		
		SAL06P-W-K	NC		
MAXXIMA	-	AAL06-C1	NC		
		MEW-DM600	OK		

DIMMER COMPATIBILITY	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.