



MODEL	ST19 7W 600LM 2200K E26
SKU	SE-RCL06.1107-B

DIMMER COMPATIBILITY LIST			
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
LUTRON	DIVA	DV-603P	OK
		DVW-600PH-WH	NC
		DV-603PH-WH	OK
		DVCL-153PH	NC
		DVCL-153P-WH	OK
		DVWCL-153PH-WHC	OK
		DV-600P-WH	NC
		DVCL-253PH	NC
		DVELV-300P-WH	OK
		S-600	NC
	D-600PH-DK	NC	
	DV-603PR	OK	
	S-600PR-WH	OK	
	S-603PGH-WH	NC	
	S-10PH	NC	
	CTCL-153P-WH	OK	
	SCL-153P-WH	NC	
	S-600-IV	OK	
	S-600-AL	OK	
	S-603PH-WH	OK	
	S-600H-WH	NC	
	SCL-153PH-WH	OK	
	S-603P-WH	OK	
	SELV-300P-WH	OK	
	SLV-600-WH	OK	
	D-600RH-DK	NC	
	TG-600PH-IV	NC	
	TGCL-153PH-WH	OK	
	MAW-600H-AL	NC	
	MACL-153M-WH	NC	
	MACL-153MR-WH	NC	
	MACL-153MH-WH	NC	
	MSCL-OP153MH-WH	NC	
	TG-603PGH-WH	NC	
	MAELV-600-WH	OK	
	MAW-600	NC	
	D-600R-IV	NC	
	DVCL-153P-WH-3	OK	
	AYCL-153P-WH	OK	
	AY-600PH-WH	NC	
	AYCL-153PH	OK	
	CT-103P-WH	OK	
	S-600P-WH	OK	
	TG-600PNLH-WH	OK	
	LECL-153PH-WH	OK	
	MACL-153MLRHW-WH	OK	
	MRF2S-6CL-WH	OK	
	PD-6WCL-WH	OK	
	SPSELV-600M	OK	
	NTSELV-300-WH	OK	
NTLV-600-277-WH	OK		
RADIO RA2	RRD-6CL-WH	OK	
-	6684	NC	
-	NO.6683	NC	
-	6631-LA	OK	
-	IPI06	NC	
-	S-600P-WH	OK	
-	NO.6672	OK	
-	603-6631-A	OK	
-	6631-A	OK	
-	NO.IPL06	NC	
-	IPI10-1LZ	NC	
-	6683-10Z	NC	
-	IPI06-1LZ	OK	
-	NO.6631	OK	
-	6681	NC	
-	R62-6674-P0W	OK	
GE	-	18024	OK
ALMOND	-	LUXDM600-12	OK
CTL	-	DM600-12-3	OK
AH	-	SDM3/1000	OK
-	-	SDM/600	NC
LEGRAND	-	HCL453PTC	NC
-	-	DAL06P-C2-K	NC
COOPER	-	TAL06P-C2-K	NC
	-	SAL06P-W-K	NC
	-	AAL06-C1	NC
MAXXIMA	-	MEW-DM600	OK
CTL	-	DM600-12-3/LED/WH	OK
ADORNE	-	ADPD453LW2	OK
-	-	ADWR703HW4	OK
EATON	-	TAL06P1-C5	OK

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.