

# 90+ LIGHTING



<b>MODEL</b>	<b>A19 9.0W 700LM 2200K E26</b>
<b>SKU</b>	<b>SE-350.163</b>

DIMMER COMPATIBILITY LIST			
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
LUTRON	VIVE	MRF2S-6CL-WH	OK
	CASETA	PD-6WCL-WH	NC
	DIVA	DV-600P-WH	OK
		DVELV-300P-WH	OK
	DIVA C+L	DVWCL-153PH-WH	OK
	MAESTRO	MAELV-600-WH	OK
		MAELV-600-WH	OK
	SKYLARK	S-603P-WH	OK
		SCL-153P-WH	OK
		SELV-300P-WH	OK
		SLV-600-WH	NC
	SPACER	SPSELV-600M	OK
	NOVA T	NTELV-300-WH	OK
		NTLV-600-277-WH	NC
	RADIO RA2	RRD-6CL-WH	OK
ARIADNI	AYCL-153P-WH	NC	
LEVITON	DECORA	R62-6674-P0W	OK
	-	R70-6631-1LW	OK

#### DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

#### 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.  
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.