

90+ LIGHTING



MODEL	G25 3.8W 350LM 2200K E26
SKU	SE-350.122

DIMMER COMPATIBILITY LIST			
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
LUTRON	VIVE	MRF2S-6CL-WH	NC
	CASETA	PD-6WCL-WH	NC
	DIVA	DV-600P-WH	NC
		DVELV-300P-WH	OK
	DIVA C*L	DVWCL-153PH-WH	OK
	MAESTRO	MAELV-600-WH	OK
		MAELV-600-WH	OK
	SKYLARK	S-603P-WH	NC
		SCL-153P-WH	NC
		SELV-300P-WH	OK
		SLV-600-WH	NC
	SPACER	SPSELV-600M	OK
	NOVA T	NTELV-300-WH	OK
		NTLV-600-277-WH	OK
	RADIO RA2	RRD-6CL-WH	OK
-	CT-600PR-WH	OK	
LEVITON	ARIADNI	AYCL-153P-WH	NC
	DECORA	R62-6674-P0W	NC
	-	R70-6631-1LW	OK
	-	C22-6672-1LW	OK

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 - 2) The results may be different for each application depending on the installation conditions.
 - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
 - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.