

90+ LIGHTING



MODEL	B11 4W 400LM 2700K E12
SKU	SE-350.194

DIMMER COMPATIBILITY LIST			
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
LUTRON	DIVA	DV-600P-WH	NC
		DVELV-300P-WH	OK
	-	MACL-153MR-WH	OK
	-	CT-600PR-WH	OK
	-	TG600P	OK
	-	T90B6	OK
	-	S600	OK
	MAESTRO	MRF2S-6CL-WH	NC
		MACL-153M-WH	OK
		MAELV-600-WH	OK
	CASETA	PD-6WCL-WH	NC
	DIVA C+L	DVWCL-153PH-WH	NC
	SKYLARK	S-603P-WH	NC
		SCL-153P-WH	NC
		SELV-300P-WH	OK
		SLV-600-WH	NC
	SPACER	SPSELV-600M	OK
		NTELV-300-WH	OK
NOVA T	NTLV-600-277-WH	NC	
	RRD-6CL-WH	NC	
Radio RA2	AYCL-153P-WH	NC	
	Ariadni	AYCL-153P-WH	NC
LEVITON	Decora	R62-6674-P0W	NC

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.